

As of January 1, 2011 DG Technologies (DG) has discontinued the development and support of the DLM software program.

DLM is now free-of-charge for all DPA customers to download and use. DLM is provided as-is and DG disclaims all warranties either express or implied, including any implied warranty of merchantability or fitness for a particular purpose. DG makes no warranty or guaranty as to the performance of the DLM product. DG has heard customer successes using DLM on operating systems up to Microsoft Windows 7 64-bit.

Prepping Your PC and Installing DLM

- ⊕ Uninstall all **Dearborn Group**, **Dearborn**, or **DG Technologies** entries using the Windows Control Panel.
- ⊕ Download and run the following program to remove any references to old DPA installations:
 - [KillDGInstall.zip](#)
 - Click **Start Search**. After it is finished, click **Delete Files** and answer **Yes** to the prompts.
 - Ignore any error messages.
- ⊕ Download and install the latest DPA 4 Plus legacy drivers (DG121032) from this page:
 - [DPA 4 Plus Download Page](#)
- ⊕ Download and install the latest DLM version from this link:
 - [DLM Installation](#)

DO NOT CHOOSE THE OPTION TO INSTALL DRIVERS. DLM WILL NOT WORK!!!

Configuration of DLM – Device Identifiers (Device IDs) Have Changed

- ⊕ To find the correct DeviceID to use, look at the file **c:\windows\dg_dpa32.ini**.
 - The default USB entry is 150. This will work with any DPA product with a USB port.
 - The default entry for serial port DPAs (DPA II/DPA II Plus/DPA III Plus) attached to **COM1** is **101**.

DLM and the DPA 5

- ⊕ DLM will work with the DPA 5 using the native drivers installed as part of the DG121032 drivers (above), however you will have to select the correct DeviceID.
 - To find the correct DeviceID to use, look at the file **c:\windows\dg_dpa32.ini**.
 - The default USB entry is 150. Even though the DPA 5 is not listed, this entry functions properly.

Full-Featured Alternative Products from DG

If you cannot get the DLM product to work, or you are looking for more advanced functionality, DG recommends our full-featured and supported software application called **Hercules**. This software is available for all of our **Gryphon** and **S3/S4** line of hardware products. For more information on these products, contact a DG sales associate at 248-888-2000.



33604 West 8-Mile Road
Farmington Hills, MI 48335
(248)-888-2000
techsupp@dgtech.com